

Smart Relay



Bluetooth Control



Smart On/Off



High Power Load



Built-in Energy Meter

Recommended to use in **renovation projects**; able to connect non-smart luminaires to our smart lighting system.





Smart Relay



Bluetooth Control



Smart On/Off



High Power Load



Built-in Energy Meter

Specification

Item Code	Item Description
821017003800	LEDSmart-BLE2-Relay-1000W

Technical Specification	
IP-class	IP20
Protection Class	II
Finishing	White RAL9003
Communication	Opble Bluetooth® Low Energy Mesh
Max. Switching capacity	1000W LED
Max. Load	1000W LED

Electrical Supply	
Nominal Voltage	220-240VAC
Max. inrush or surge current I _p (20 ms)	120 A
Frequency	50/60Hz
Connection cable	0.75-2.5mm ²

Mechanical Properties	
Housing Material	PC

Application Conditions	
Application Temperature	+25°C

Packaging Information

Item		Outer box		
Item Code	Item Description	Dimensions(mm) (LxWxH)	Gross Weight (kg)	Packing Qty (pcs/CTN)
821017003800	LEDsmart-BLE2-Relay-1000W	365*245*120	3.78	36

Dimensional Drawing (mm)

